

**ADDRESSING AND CONTROL:**

- SEQUENTIAL: EACH NODE IS UNIQUELY ADDRESSED AND REQUIRES 3 CONSECUTIVE DMX CHANNELS. ALL 3 CHANNELS SHOULD BE ADJUSTED SIMULTANEOUSLY TO DIM THE NODES.
- ALL SAME ADDRESS: THE ENTIRE STRING (ALL 50 NODES) IS CONTROLLED BY 3 CONSECUTIVE DMX CHANNELS. ALL 3 CHANNELS SHOULD BE ADJUSTED SIMULTANEOUSLY TO DIM THE NODES.
- PDS BASE LIGHT NUMBER CANNOT EXCEED 10 FOR SEQUENTIAL ADDRESSING
- PDS BASE LIGHT NUMBER CANNOT EXCEED 60 FOR ALL SAME ADDRESS MODE

**NOTE:**

- USE A THIRD PARTY DMX REPEATER ON EVERY 32nd PDS UNIT IN A CHAIN, OR WHEN THE TOTAL DMX DATA RUN EXCEEDS 1,000 FEET. REFER TO THE USITT DMX-512 STANDARD FOR MORE INFORMATION.
- MAXIMUM NUMBER OF LIGHT NODES PER PDS-60ca 24V: 50 (USE OUTPUT 1).
- DO NOT SHORTEN OR LENGTHEN LEADER CABLE. CUTTING THE LEADER CABLE WILL DAMAGE THE DATA DRIVE CIRCUITRY.

**PHILIPS**


COPYRIGHT © 2007 PHILIPS SOLID-STATE LIGHTING SOLUTIONS. ALL RIGHTS RESERVED. CHROMACORE, CHROMABLOC, OR THE CK LOGO, COLOR KINETICS, THE COLOR KINETICS LOGO, COLOR KINETICS THE LEDS IN INTELLIGENT LIGHT, COLORBLAST, COLORBLAZE, COLORBUZZ, COLORCAST, COLORPLAY, COLORSCAPE, COLORSTRIKE, COLOR TUBE, ESSENTIALWHITE, HYPERCOLOR, ICA OR COVE, INTELLIWHITE, IP-PLAYER, LIGHT WITHOUT LIMITS, OPTIM, POWERCORE, SUBFLUX, SPACE, THE SPACE LOGO, AND SMARTFACE ARE EITHER REGISTERED TRADEMARKS OR TRADEMARKS OF PHILIPS SOLID-STATE LIGHTING SOLUTIONS IN THE UNITED STATES AND/OR OTHER COUNTRIES. ALL OTHER BRAND OR PRODUCT NAMES ARE TRADEMARKS OR REGISTERED TRADEMARKS OF THEIR RESPECTIVE OWNERS.

**DATA TERMINATOR**



PLACE IN DMX LOOP OUT PORT OF POWER/DATA SUPPLY WHEN REQUIRED (SEE NOTES)

**CAT5/RJ45 PINOUT**



(VIEW FACING PINS)

TITLE: SYSTEM WIRING DIAGRAM (TYP)

PRODUCTS: eW FLEX SLX/PDS-60ca 24V DMX/ETHERNET/ COLORDIAL/PS-60

DATE: 8-1-2008

DWG. BY: BHG

SCALE: NTS

REV:

PAGE: 1 OF 1