

CONTINUE DMX OUT/IN SEQUENCE TO INCLUDE ALL PWR/DATA SUPPLIES, THEN TERMINATE THE LAST UNIT (SEE BELOW)


CAT 5/RJ45 DATA CABLE (UTP 24 AWG 4 PAIR)

NOTE:

- USE A THIRD PARTY DMX REPEATER ON EVERY 32nd PDS UNIT IN A CHAIN, OR WHEN THE TOTAL DMX DATA RUN EXCEEDS 1,000 FEET. REFER TO THE USITT DMX-512 STANDARD FOR MORE INFORMATION.
- MAXIMUM NUMBER OF LIGHT NODES PER PDS-60ca: 100 (50 PER OUTPUT).
- DO NOT SHORTEN OR LENGTHEN LEADER CABLE. CUTTING THE LEADER CABLE WILL DAMAGE THE DATA DRIVE CIRCUITRY.

DATA TERMINATOR

PLACE IN LAST DMX OUT PORT OF POWER/DATA SUPPLY CHAIN



COLOR KINETICS INCORPORATED
10 MILK STREET, SUITE 1100
BOSTON, MA 02108
888 FULL RGB
617 423 9999
WWW.COLORKINETICS.COM
"FULL SPECTRUM DIGITAL LIGHTING"

TITLE: SYSTEM WIRING DIAGRAM (TYP)	DATE:
PRODUCTS: Flex SL /PDS-60ca 7.5V / DMX Adapter Cable	DWG. BY: C.F.
	SCALE: NTS
	REV:
	PAGE: 1 OF 1