


**CAUTION:** CONNECT ONLY 1 FIXTURE RUN (12 L.F.) TO A FUSE GROUP

- NOTES:**
- EACH PDS-150e WILL SUPPORT TWO (2) RUNS OF iCOLOR FRESOCO.
  - EACH RUN CAN CONTAIN A MAX. OF 12 LINEAR FT. OF iCOLOR FRESOCO FIXTURES, FOR A TOTAL OF 24 L.F. PER PDS-150e.
  - USE 3 CONDUCTOR, 14-16 AWG LEAD CABLES (SUPPLIED BY OTHERS) FROM PDS-150e TO FIRST JUNCTION BOX.
  - MAX. CABLE RUN FROM PDS-150e TO LAST LIGHT: 50 FEET (15M).

CONTINUE DMX OUT/IN SEQUENCE TO INCLUDE ALL PWR/DATA SUPPLIES, THEN TERMINATE THE LAST UNIT (SEE BELOW)

**DATA TERMINATOR**



PLACE IN DMX LOOP OUT PORT OF POWER/DATA SUPPLY WHEN REQUIRED (SEE NOTES)

**NOTE:**

- USE DMX OUT REPEATER (INSTEAD OF LOOP OUT) ON EVERY 32nd PDS UNIT IN A CHAIN, OR WHEN A DATA CABLE RUN BETWEEN UNITS EXCEEDS 400'.
- WHEN USING THE DMX OUT REPEATER, PLACE A DATA TERMINATOR IN THE DMX LOOP OUT PORT OF THAT PDS UNIT (SEE ABOVE).