



CONTINUE DMX OUT/IN SEQUENCE TO INCLUDE ALL DATA ENABLERS, THEN TERMINATE THE LAST UNIT WITH DATA TERMINATOR (SEE BELOW)




12AWG 4-C CABLE (BY OTHERS)



12AWG 4-C CABLE (BY OTHERS)

US: RED DATA LINE, BLACK NEUTRAL, WHITE GROUND
 EUROPE: RED DATA LINE, BROWN NEUTRAL, BLUE GROUND, GREEN/YELLOW



NOTE:
 -USE A THIRD PARTY DMX REPEATER ON EVERY 32nd DATA ENABLER IN THE DAISY CHAIN OR WHEN THE TOTAL DMX DATA RUN EXCEEDS 1000 FEET (300m). REFER TO THE RECOMMENDED PRACTICES FOR DMX512 FOR FURTHER INFORMATION REGARDING INSTALLATIONS UTILIZING DMX512 CONTACT TECHNICAL SUPPORT FOR RECOMMENDED THIRD PARTY DMX REPEATERS.
 -PLACE A DATA TERMINATOR IN THE DMX LOOP OUT PORT OF THE LAST PDS UNIT IN THE DAISY-CHAIN.
 -COLOR REACH POWERCORE HAS 2 LIGHT ADDRESSES PER FIXTURE. PHILIPS PLAYER 3 OR SMARTJACK PRO IS REQUIRED TO ADDRESS FIXTURES.
 -REFER TO PRODUCT INSTALLATION GUIDE FOR ADDITIONAL DETAIL ON FIXTURE CONNECTION AND MOUNTING.
 -MAXIMUM NUMBER OF FIXTURES PER DATA ENABLER:
 -5 @ 100V, 6 @ 120V, 12 @ 240V
 -MULTISYNCHRONIZER CAN SUPPORT UP TO 12 LIGHT ADDRESSES.


DATA TERMINATOR

CAT5/RJ45 PINOUT

TITLE:

SYSTEM WIRING DIAGRAM (TYP)

DATE: 12-5-2008



Copyright © 2008 and/or subsequent Philips Lighting Solutions. All rights reserved. This document is the property of Philips Lighting Solutions. It is intended for use by Philips Lighting Solutions customers only. It is not to be distributed, copied, or reproduced in any form without the prior written permission of Philips Lighting Solutions. Philips Lighting Solutions is not responsible for any damage or injury resulting from the use of this document. Philips Lighting Solutions is not responsible for any damage or injury resulting from the use of this document. Philips Lighting Solutions is not responsible for any damage or injury resulting from the use of this document.

PLACE IN DMX LOOP OUT PORT OF POWER/DATA SUPPLY WHEN REQUIRED (SEE NOTES)

(VIEW FACING PINS)

PRODUCTS:

COLOR REACH POWERCORE/DATA ENABLER/
 MULTISYNCHRONIZER/PS-60

SCALE: NTS
 REV: 1
 PAGE: 1 OF 1